

#### DESCRIPTION

Smart disk light supports surface mounting and retrofit installation. Support remotely control, when you go out and forget to turn off the lights, open your phone to easily turn off the lights. Support voice system control, free your hands and turn off lights easily in everywhere at home. Color: RGB+Warm White+Cold White. Suitable for Wet Locations, perfect for new construction project: entrance, hallways, kitchens, bathrooms, closets, laundry, porches and garage work rooms and more.















#### **FEATURES**

Download the "Smart Life" or "tuya" APP to connect and enjoy intelligent control. NOTE: Only support 2.4 GHz Wi-Fi.

- 16 million colors availiable.
- Support Bluetooth+WIFI+Voice control.
- Control the light in groups.
- Timer function, setting lights on/off automatically.
- Multi preset scene modes and DIY scenes to fits any occasions.

### INSTALLATION

With multiple apertures, can be installed into any 5 or 6 inch recessed can, or any 3.5 inch junction box.

## DIMMING

Compatible with most triac dimmers to give user a smooth 100%-5% dimming to choose the desired brightness.

### **ELECTRICAL**

This fixture is built with the highest quality 120V drivers, ensuring energy efficiency.

#### **SPECIFICATION**

Model: 6HVCT12DWHS

Size: 6inch Wattage: 12W Lumens: 1031Lm Voltage: 120V

Power Frequency: 60Hz

Power Factor: >0.9

CCT: RGB+(2700K~6500K)

CRI: 90

Beam Angle: 120° Material: PC+Iron

Lifespan: ≥50,000hours

Operating Temp: (-4°F~ 122°F) -20~40°C

Dimmable: Triac Dimming

Rating: Suitable for Wet Locations

Warranty: 5 year limited

## **ENERGY SAVINGS**

80% more energy savings than halogen lamps.

### LISTING

FCC.FCC-ID.














Color: Warm White+Cold White Brightness can be adjusted from 1% to 100%.



Color: RGB Brightness can be adjusted from 1% to 100%.



Work with Amazon Alexa / Google Home.




Timer function, setting lights on/off automatically.





**a** 








SURFACE MOUNT ACCESSORIES				
PART	DESCRIPTION	QUANTITY		
c d	Wire Nuts Screws	3 2		

RETROFIT INSTALLATION ACCESSORIES				
PART	DESCRIPTION	QUANTITY		
а	E26 Adapter	1		
b	Mounting Springs	2		
C	Wire Nuts	3		

# SIZE & DIMENSION





Size	А	В	С
6inch	Φ7.22"(183.5mm)	0.87"(22.2mm)	1.36"(34.4mm)